



# KSQ CIRCULAR COMBINATION CAM LOCKER LOCK

## KSQ-7450 CL

### USER INSTRUCTIONS FOR KSQ 7450 CL



1. The factory default combination of the KSQ 7450 CL is 0-0-0-0
2. After installing and testing the lock with the default combination it is highly recommended for security purposes to change the default combination to a new combination.
3. With the door open at all times during the setting of a new combination, make sure the knob is in the unlocked position which is identified by the unlocked padlock icon at the top of the lock face.
4. Write down your new 4-digit combination and make sure the current or default combination is correctly displayed and aligned in the middle row of the dial window and in correct numeric sequence e.g. 0-0-0-0
5. Insert the small silver change key supplied separately with the lock into the slotted screw located on the right hand side of the lock at 3 o'clock and rotate the screw 90 degrees clockwise
6. Dial up your new 4-digit combination making sure it is in the middle row and in your new combination correct numeric sequence e.g. 1-2-3-4 then rotate the change screw back anti-clockwise 90 degrees to set the new combination. Do not close the door until you have tested both the locking and unlocking functions 2-3 times using your new combination.
7. To lock the lock, close the locker door and scramble the 4 dials to conceal of your combination, then rotate the outer black knob counter-clockwise to the 9 o'clock position identified by the locked padlock icon to lock it.
8. If the combination is forgotten or has been change and is unknown, insert the master override key supplied with the lock/s and rotate the key clockwise, with the key still in the lock, rotate each combination dial individually until it stops. When all 4 dials have been rotated and stop, the combination will be revealed. Rotate the master override key counter-clockwise and remove it. Now that you have the unknown combination you may change it as per above instructions or continue operating the lock using the original revealed combination

**PLEASE NOTE:** Keep the master override key and the combination change key on the same key ring and store them in a secure place where you can access them in the future. For technical support contact your reseller supplier.

**WARRANTY:** The KSQ 7450 CL is warranted against materials and manufacturing defects for 12 months from date of supply excluding normal wear and tear, forced opening, vandalism, misuse or incorrect operation and physical damage



KSQ-7450 C



September 2021  
ABN 61 102 798 381

DISCLAIMER: KeyWatch Systems QLD reserve the right to make any changes without notice to colour, dimensions, pricing and technical specifications. Please confirm prior to ordering.

KEYWATCH SYSTEMS QLD

PH (07) 5600 0821

sales@ksq.com.au

www.ksq.com.au